3752RK

Creative Touch 3-Series 75" interactive flat panel display

Optoma





- Advanced interaction and collaboration -CreativeCast Pro interactive wireless collaboration toolset
- Advanced touch technology Pen and finger recognition for a seamless experience
- Dual App mode Run two applications at the same time on the screen
- Safe and secure viewing experience Anti glare and anti finger print, low blue light and flicker free TUV certified

Robust collaboration, extensive connectivity options and a valuefocused design. Combining the latest technology and packed with everything a classroom or business requires, the Creative Touch 3-Series delivers all the functionalities and processing power needed to create, educate and collaborate.



Easily access the front-facing ports for HDMI and USB connectivity. For wireless connectivity, Optoma's CreativeCast Pro allows up to four users to share content at the same time from their Windows, iOS, macOS, Chrome or Android devices.

Specifications

| Display | |
|--|---|
| Back light | Direct type LED |
| Size (diagonal) | 75" |
| Resolution | 3840x2160 |
| Brightness | 400 |
| Contrast ratio (dynamic) | 5,000:1 |
| /iewing angle | 178° |
| Response time | 6ms |
| .ife Display colours | 50,000 hours 1.070 |
| Speaker count | 2 |
| Vatts per speaker | 20W |
| Surface hardness | 9H |
| alass | Anti Glare + Anti Finger Print / HAZE: 4-8% |
| Municent light sensor | Yes |
| Air gap | 4.00mm |
| Pencil hardness | 9H |
| Physical spec | |
| Dimensions (W x D x H) mm | 1735 x 116 x 1047 |
| Vall-hanging screw spec | M8*25mm |
| /ESA holes | 800x400 |
| In the box | European Standard Power Cord |
| | American Standard Power Cord British Standard Power Cord |
| | USB Cable |
| | HDMI Cable |
| | Writing Pen x2 Remote Control |
| | Battery |
| | Pen holder/ Pen tray |
| | QSG |
| Connections | Inputs 3 x HDMI 2.0, 1 x VGA, 1 x DisplayPort, 1 x Audio |
| | 3.5mm, 4 x USB 2.0, 1 x USB 3.0, 1 x RJ45, 1 x USB-C, 1 x Microphone |
| | Outputs 1 x HDMI 2.0, 1 x S/PDIF, 1 x Audio 3.5mm, 1 x |
| | RJ45 |
| | Control 2 x USB-B interactive, 1 x RS232 |
| Bezel size (top) | 22.00mm |
| Bezel size (top) | 54.00mm |
| Bezel size (left) | 22.00mm |
| Bezel size (right) | 22.00mm |
| Operating conditions | 20% ~ 93% RH |
| Dperating temperature (min) | -10°C |
| Operating temperature (max) | 45°C |
| let weight | 51 kg |
| aross weight | 65 kg |
| Vireless - technology | Wifi 6, 2.4G/5G, 2T2R, BT5.2 (AZ832-HN optional) |
| Vireless - operating frequency | 2.4G/5G |
| ouch system | |
| | Windows10/Windows8/Windows7/Windows XP /Linux/Mac (1 |
| System | |
| System | Touch point only)/Android/Chrome |
| ouch accuracy | Touch point only)/Android/Chrome <1.00mm |
| ouch accuracy ouch point | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows |
| System Fouch accuracy Fouch point Fouch tool | Touch point only)/Android/Chrome <1.00mm |
| ouch accuracy ouch point | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen |
| System Fouch accuracy Fouch point Fouch tool Pen/finger detection | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen |
| System Jouch accuracy Jouch point Jouch tool Pen/finger detection | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes |
| System Fouch accuracy Fouch point Fouch tool Per/finger detection Power Power supply | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A |
| System Fouch accuracy Fouch point Fouch tool Pen/finger detection Power Power supply Power consumption (standby) | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W |
| System Souch accuracy Souch point Souch tool Pen/finger detection Power censumption (standby) Power consumption (max) Power consumption - average watts) | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W 400W |
| System Souch accuracy Souch point Souch tool Pen/finger detection Power Power consumption (standby) Power consumption (max) Power consumption - average watts) Peration System | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W 400W 153.1 |
| System Souch accuracy Souch point Souch tool Pen/finger detection Power supply Power consumption (standby) Power consumption (max) Power consumption - average watts) Peration System System version | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W 400W 153.1 Android 11 |
| System Souch accuracy Souch point Souch tool Souch tool Sower detection Sower consumption (standby) Sower consumption (max) Sower consumption - average watts) Soperation System System version SPU | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W 400W 153.1 Android 11 Quad-core A55 |
| System Fouch accuracy Fouch point Fouch tool Fouch tool Power detection Power consumption (standby) Power consumption (max) Power consumption - average watts) Poperation System System version CPU SPU | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W 400W 153.1 Android 11 Quad-core A55 Dual-cord A52 |
| System Fouch accuracy Fouch point Fouch tool Fouch tool Four eterction Forwer Power consumption (standby) Power consumption (max) Power consumption - average watts) Poperation System System version CPU SAM | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W 400W 153.1 Android 11 Quad-core A55 Dual-cord A52 4GB |
| System Fouch accuracy Fouch point Fouch tool Pen/finger detection Power Power consumption (standby) Power consumption (max) Power consumption - average watts) Poperation System System version PPU APU AAM Storage | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W 400W 153.1 Android 11 Quad-core A55 Dual-cord A52 4GB 32GB |
| System Fouch accuracy Fouch point Fouch tool Fouch tool Four eterction Forwer Power consumption (standby) Power consumption (max) Power consumption - average watts) Poperation System System version CPU SAM | Touch point only)/Android/Chrome <1.00mm 20 android / 40 windows Finger, Passive infrared pen Yes 100-240V~ 50/60Hz 3.5A 0.5W 400W 153.1 Android 11 Quad-core A55 Dual-cord A52 4GB |







Copyright © 2023, Optoma and its logo is a registered trademark of Optoma Corporation. Optoma Europe Ltd is the licensee of the registered trademarks or registered trademarks of their respective owners. Errors and omissions excepted images are for representation purposes only and may be simulated. 27062023101600